



SERIES 9900 WIRELESS INTERCOM SYSTEM

VOX BELT STATION

U9913-BSW

PURGING INSTRUCTIONS



SERIES 9900 WIRELESS INTERCOM SYSTEM

First, turn off the Belt Station power by pressing the power button on the side of the unit



POWER
BUTTON



SERIES 9900 WIRELESS INTERCOM SYSTEM

Next, push and hold the PTT switch on the front of the unit.



PTT BUTTON



SERIES 9900 WIRELESS INTERCOM SYSTEM

Then, push and **hold** the power button, powering the unit up, **while continuing to hold the PTT switch**



PTT BUTTON

POWER
BUTTON



SERIES 9900 WIRELESS INTERCOM SYSTEM



To complete the process, when the LED indicator turns **red**, release the power button...



PTT BUTTON

POWER
BUTTON

...then release the PTT switch. The LED indicator will **flash red** for 15 to 20 seconds, followed by a voice prompt, "Connection Deleted."

